

IC-A16

VHF AIR BAND TRANSCEIVER

8.33/25 kHz Ground to Air Radio with Class Leading 1500 mW Powerful Audio









SPECIFICATIONS

	IC-A16
GENERAL	
Frequency range	TX: 118.000-136.99166 MHz RX: 108.000-136.99166 MHz RX (Weather): 161.650-163.275 MHz
Number of memory channels	200 channels
Channel spacing	8.33 kHz/25 kHz
Type of emission	6K00A3E, 5K60A3E, 16K0G3E (Weather)
Power supply requirement	7.2 V DC
Current drain (approximate)	
TX High	1.8 A
RX Max. audio/Stand-by	650 mA/65 mA typical
Antenna impedance	50 Ω (BNC type antenna connector)
Operating temperature range	-10°C to +60°C, 14°F to +140°F
Dimensions (W×H×D)	52.2 × 111.8 × 34.1 mm,
(Projections not included)	$2.1 \times 4.4 \times 1.3$ in (with BP-280)
Weight (approximate)	257 g, 9.1 oz (with BP-280)
TRANSMITTER	
Output power (at 7.2 V DC)	6.0 W (PEP), 1.8 W (carrier)
Audio harmonic distortion	Less than 10% (at 60% modulation)
Spurious emissions	More than 46 dB*
Frequency stability	±0.4 kHz
RECEIVER	
Intermediate frequencies	46.35 MHz (1st), 450 kHz (2nd)
Sensitivity	COM: Less than 0 dBµ (at 6 dB S/N) NAV: Less than 3 dBµ (at 6 dB S/N) Weather: Less than –8 dBµ (at 12 dB SINAD)
Squelch sensitivity (Threshold)	Less than 0 dB μ , Weather: Less than –5 dB μ
Spurious response	More than 60 dB, Weather: More than 30 dB
Hum and noise	More than 35 dB (at 30% modulation)
	1500 mW typical More than 350 mW (AM 8 Ω 60% modulation at 10% distortion)
External speaker connector	3 conductor 3.5 (d) mm

 ^{*} Except operating frequency ±62.5 kHz in 25 kHz channel spacing. Except operating frequency ±20.825 kHz in 8.33 kHz channel spacing.

Measurements made in accordance with FCC Part 87.

All stated specifications are subject to change without notice or obligation.

Applicable U.S. Military Specifications

MIL 810G	
Method	Procedure
500.5	I, II
501.5	I, II
502.5	I, II
503.5	I–C
505.5	I
506.5	I, III
507.5	II
509.5	_
510.5	I
512.5	I
514.6	I
516.6	I, IV
	Method 500.5 501.5 502.5 503.5 505.5 506.5 507.5 509.5 510.5 512.5 514.6

Also meets equivalent MIL-STD-810-C, -D, -E and -F.

Ingress Protection Standard	
Dust and Water	IP67/IP54

Supplied accessories:

BP-280 battery pack
 BC-213 rapid charger
 BC-242 AC adapter
 FA-B02AR antenna
 MB-133 belt clip
 Hand strap

OPTIONS

BATTERY PACKS

BP-278 Rechargeable Li-ion 7.2 V 1190 mAh (typ.), 1130 mAh (min.).

BP-279 Rechargeable Li-ion 7.2 V 1570 mAh (typ.), 1485 mAh (min.).

BP-280 Rechargeable Li-ion 7.2 V 2400 mAh (typ.), 2280 mAh (min.). Same as supplied.



▲BP-278



▲BP-279



DESKTOP CHARGER

BC-213 Charges the BP-278, BP-279 or BP-280. Same as supplied.

BC-242 AC adapter. Same as supplied.

BC-123SA AC adapter.

BC-242



MULTI-CHARGER

BC-214* Charges up to six batteries (with/without transceivers) at the same time.

BC-157S AC adapter.

* The AD-130 charger adapters are supplied with the BC-214, depending on the charger version.



VEHICLE CHARGER CABLE CP-23L For use with the BC-213.





CHARGER BRACKET MB-130 For use with the BC-213.













MB-96N Swivel type. MB-96F Fixed type. MB-96FL Longer type ▲MB-96F ▲MB-96FL

ANTENNA FA-B02AR Same as supplied.

SOFTWARE AND CABLE CS-A16 Programming software for Windows® PC.

OPC-478UC USB type transceiver programming cable.

Icom, Icom Inc. and Icom Iogo are registered trademarks of Icom Incorporated (Japan) in Japan, the United States, the United Kingdom, Germany, France, Spain, Russia, Australia, New Zealand, and/or other countries. Windows is either a registered trademark or a trademark of Microsoft Corporation in the United States and/or other countries. The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Icom Inc. is under license. All other trademarks are the properties of their respective holders.

Icom Inc.

1-1-32, Kamiminami, Hirano-Ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

www.icom.co.jp/world

Count on us!

Icom America Inc. www.icomamerica.com

Icom Canada www.icomcanada.com

Icom Brazil

E-mail: sales@icombrazil.com

Icom (Europe) GmbH www.icomeurope.com

Icom Spain S.L. www.icomspain.com

Icom (UK) Ltd. www.icomuk.co.uk

Icom France s.a.s. www.icom-france.com

Icom (Australia) Pty. Ltd. www.icom.net.au

Shanghai Icom Ltd. www.bjicom.com

Your local distributor/dealer: